# REED SWITCH ORD312

# High Power Long Life

# GENERAL DESCRIPTION

The ORD312 is a small single-contact reed switch designed for general control of medium level loads less than 200 V. The contacts are sealed within the glass tube with inert gas to maintain contact reliability.

## FEATURES

- (1) Reed contacts are hermetically sealed within a glass tube with inert gas and do not receive any influence from the external atmospheric environment.
- (2) Quick response
- (3) The structure comprises the operating parts and electrical circuits arranged coaxially. Reed switches are suited to applications in radio frequency operation.
- (4) Reed switches are compact and light weight.
- (5) Superior corrosion resistance and wear resistance of the contacts assures stable switching operation and long life.
- (6) With a permanent magnet installed, reed switches economically and easily become proximity switches.

## EXTERNAL DIMENSIONS (Unit: mm)



# APPLICATIONS

- Automotive electronic devices
- Control equipment
- Communication equipment
- Measurement equipment
- Household appliances

# ■ ELECTRICAL CHARACTERISTICS

1	
Rated value	Unit
10~30	AT
5min	AT
100max	mΩ
250min	VDC
10 <sup>9</sup> min	Ω
0.3max	pF
30	VA
200DC 100AC	V
0.5	A
1.0	A
	10~30 5min 100max 250min 10 <sup>9</sup> min 0.3max 30 200DC 100AC 0.5

## (1) Drop-out Value vs. Pull-in Value



#### (2) Contact resistance



#### (3) Breakdown voltage







3

(5) Electrostatic capacitance



# OPERATING CHARACTERISTICS

Parameter	Rated value	Unit
Operate time	0.4max	ms
Bounce time	0.3max	ms
Release time	0.05max	ms
Resonant frequency	5900±400	Hz
Maximum operating frequency	500	Hz

(1) Operate time



(3) Release time



(2) Bounce time



#### (4) Resonant frequency



## MECHANICAL CHARACTERISTICS

(1) Lead tensile test (static load)





#### (2) Lead tensile strength

# ENVIRONMENTAL CHARACTERISTICS

(1) Temperature characteristics



(2) Temperature cycle

#### (3) Temperature and humidity cycle



3

(6) Shock test











2) Misoperation area

# ■ LIFE EXPECTANCY DATA: ORD312





(%) 99.9 No failure 90 70 100mA 10mA 5mA Cumulative failure rate 50 30 10 5 1 0.1 5 7 10<sup>6</sup> 5 7 10<sup>8</sup> 2 5 7 10<sup>9</sup> 0 2 3 2 3 5 7 10<sup>7</sup> 2 3 3 Number of operations

\* Arrow indicates number of operations where test was completed.

(%) 99.9 Cumulative failure rate 200mA 100mA 150mA 50mA 10mA 90 70 50 30 10 5 1 0.1 0 2 3 5 7 10<sup>5</sup> 23 5 7 10<sup>6</sup> 2 3 5 7 10 2 3 5 7 10<sup>8</sup> Number of operations

\* Arrow indicates number of operations where test was completed.

Voltage: 5VDC Current: 100µA, 10mA, 20mA Load: Resistive load

Load conditions Voltage: 12VDC Current: 5mA, 10mA, 100mA Load: Resistive load

Load conditions Voltage: 200VDC Current: 10mA, 50mA, 150mA Load: Resistive load