Shock-Safe Fuseholder, 5 x 20 / 6.3 x 32 mm, Slotted Cap/Fingergrip, IEC: 500 VAC, UL/CSA: 600 VAC/DC





Socket with Slotted Cap Caps must be ordered separately (see accessories)

Socket with Fingergrip Cap

500 VAC · 4/ 3.2 W / 10 A (VDE) · 600 VAC/DC · 20 A (UL/CSA)

See below:

Approvals and Compliances

Description

- Fuseholder for 500 VAC applications
- Cap is available slotted or with fingergrip
- 5x20: 3.2W / 6.3x32: 4W

Applications

- Equipment with three-phase supply (400 VAC)

pdf datasheet, html-datasheet, General Product Information, Packaging details, Distributor-Stock-Check, Accessories, Detailed request for product, Microsite

Technical Data	
Shock-Safe Category	PC2
Fuse-Link	5 x 20 or 6.3 x 32 mm
Mounting	Panel Mount, Front Side
Attachment	Fixing Nut
Terminal	Solder or Quick-Connect 6.3 x 0.8 mm
Rated Voltage	500 VAC (VDE), 600 VAC/DC (UL/CSA)
Rated current	10A (VDE), 20A (UL/CSA)
Rated Power Acceptance IEC	4/3.2W / 10 A @ Ta 23°C
	Admissible power acceptance at higher
	ambient temperature see derating cur-
	ves
Degree of Protection	IP 40
Protection Class	Suitable for appliances with protection
	class I acc. to IEC 61140
Admissible Ambient Air Temp.	-40 °C to 85 °C
Climatic Category	40/085/21 acc. to IEC 60068-1

Thermoset, black, UL 94V-0

0°C to 60°C, max. 70% r.h.

Type, Rated Voltage, Power Rating,

Tin-Plated Copper Alloy

Rated current, Approvals

9 g / 5.36 g

Soldering Methods	Iron
	Soldering Profile
Solderability	350°C / 2 sec acc. to IEC 60068-2-20,
	Test Ta, method 2
Resistance to Soldering Heat	350°C / 10 sec acc. to IEC 60068-2-20,
	Test Tb, method 2
Contact Resistance	≤ 10 mΩ at 20 mV acc. to IEC 60127-6
Dielectric Strength	> 3kV
	> 4 kV between life parts
	(50 Hz: 1 min)
Impulse Withstand Voltage	> 4 kV between life parts
	> 6 kV between life parts
Insulation Resistance	$> 10\text{M}\Omega$ between life parts
	$> 100 \text{M}\Omega$ between life parts
	(500 VDC: 1 min)
Overvoltage Category	Il acc. to IEC 60664-1
Pollution Degree	2 acc. to IEC 60664-1
Admissible Torque on Fixing	max 1.2Nm
Nut	
Panel Thickness	max 9mm
	·

Approvals and Compliances

Detailed information on product approvals, code requirements, usage instructions and detailed test conditions can be looked up in Details about Approvals

Approvals

Material: Socket

Unit Weight

Material: Terminals

Storage Conditions

Product Marking

The approval mark is used by the testing authorities to certify compliance with the safety requirements placed on electronic products. Approval Reference Type: FEC

Approval Logo	Certificates	Certification Body	Description
VDE	VDE Approvals	VDE	VDE Certificate Number:
c SU °us	UL Approvals	UL	UL File Number: E39328

Product standards

Product standards that are referenced

Organization	Design	Standard	Description
<u>IEC</u>	Designed according to	IEC 60127-6	Miniature fuses. Part 6. Fuse-holders for miniature fuse-links
(UL)	Designed according to	UL 4248-1	Fuseholder general requirements
CSA Group	Designed according to	CSA C22.2 no. 4248.1	Fuseholder general requirements

Application standards

Application standards where the product can be used

Organization	Design	Standard	Description
<u>IEC</u>	Designed for applications acc.	IEC/UL 60950	IEC 60950-1 includes the basic requirements for the safety of information technologyequipment.
<u>IEC</u>	Designed for applications acc.	IEC 60335-1	Safety of electrical appliances for household and similar purposes. Meets the requirements for appliances in unattended use. This includes the enhanced requirements of glow wire tests acc. to IEC 60695-2-12 and -13.


Compliances


The product complies with following Guide Lines

Identification	Details	Initiator	Description
C€	CE declaration of conformity	SCHURTER AG	The CE marking declares that the product complies with the applicable requirements laid down in the harmonisation of Community legislation on its affixing in accordance with EU Regulation 765/2008.
RoHS	RoHS	SCHURTER AG	EU Directive RoHS 2011/65/EU
50)	China RoHS	SCHURTER AG	The law SJ / T 11363-2006 (China RoHS) has been in force since 1 March 2007. It is similar to the EU directive RoHS.
REACH	REACH	SCHURTER AG	On 1 June 2007, Regulation (EC) No 1907/2006 on the Registration, Evaluation, Authorization and Restriction of Chemicals 1 (abbreviated as "REACH") entered into force.
00	White paperGlow wire test	SCHURTER AG	Meets the requirements of IEC 60335-1 for appliances in unattended use. This includes the enhanced requirements of glow wire tests acc. to IEC 60695-2-12 and -13.

Dimension [mm]

d 56.5 mm







Variant with slotted cap 0031.1631 + 0031.1611/1613


Variant Fingergrip 0031.1631 + 0031.1616





Mounting holes

Derating Curves



All Variants

Holder	Сар	Fuse-Link	Terminal	Degree of Pro- tection	Remark	Order Number
•	-	5 x 20 or 6.3 x 32mm	Solder	IP 40	-	0031.1631
•	-	5 x 20 or 6.3 x 32mm	Quick-Connect 6.3 x 0.8 mm	IP 40	-	0031.1623
•	slotted	6.3 x 32mm	Quick-Connect 6.3 x 0.8 mm	IP 40	0031.1623 + 0031.1613	0031.1622
•	Fingergrip	6.3 x 32mm	Quick-Connect 6.3 x 0.8 mm	IP 40	0031.1623 + 0031.1616	0031.1624
•	slotted	5 x 20mm	Quick-Connect 6.3 x 0.8 mm	IP 40	0031.1623 + 0031.1611	0031.1621
•	slotted	5 x 20mm	Solder	IP 40	0031.1631 + 0031.1611	0031.1632
•	slotted	6.3 x 32mm	Solder	IP 40	0031.1631 + 0031.1613	0031.1633
•	Fingergrip	6.3 x 32mm	Solder	IP 40	0031.1631 + 0031.1616	0031.1634

Most Popular.

Availability for all products can be searched real-time:https://www.schurter.com/en/Stock-Check/Stock-Check-SCHURTER

Packaging Unit Bulk (50 pcs.)

Required Accessory

Description



Caps to FEC Caps to Holder FEC